



Lexmark MB2236, B2236 | Printer Kit

STEP A **CONNECTING THE PRINTER**

When Connecting by Network:
Connect one end of the cable into the router, and the other end into the rear of the Printer (Check and Ensure the green light next to the Network Cable is flashing green – if it is not this means the port at the router or wall isn't working and needs checking).

When Connecting by USB:
Plug in one end of the USB cable into the printer, and the other end into the Computer.

STEP B **FOR WIRELESS CONNECTIONS**

Power on Printer:
Select on the screen, Settings > Network/Ports > Wireless > Wi-Fi Protected Setup > Start Push Button Method
Then Press the WPS button on the wireless router and the printer will Auto connect.

STEP C **CHECK THAT THE PRINTER HAS AN IP ADDRESS**

Settings > Network/Ports > Network settings > TCP/IP v4 > Note down the IP address

STEP D **DOWNLOADING THE CORRECT DRIVER**

Check your PC version:

For Windows: Go to the "Search Bar" enter "dxdiag", then select the top option > Note down the Operating system and version if 32/64bit.

For Mac OS version: Click the Apple logo > About this Mac > And note the Mac OS version.

When downloading drivers, ensure to select the correct OS version (if windows 32/64bit) from the Operating System Drop Down.

Driver Link [https://www.inkmasters.net.au/\[36ppm\]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-](https://www.inkmasters.net.au/[36ppm]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-)

STEP E **INSTALLING THE PRINTER FOR WINDOWS**

For Windows download the G2 Postscript print driver.
On your windows computer Run and extract the downloaded file. You will see the Add printer Wizard.

For Network Setup: Select printer I want isn't listed > TCP/IP option > Enter printer IP and port will autofill > Next and select the model series as Lexmark xc2400 > Select Do not share and give a printer name to install

For USB Setup: The Add printer Wizard will detect the printer > If printer model is correct > Click Next and select driver series > Proceed same as above

INSTALLING THE PRINTER FOR MAC

For Mac download the PS print driver.
On your Mac computer click the Apple Logo > Systems Preferences > Printers and Scanners > + button.

AirPrint: In the Default tab select the printer model (where it says Bonjour Multifunction next to the model) > Select the installed driver in use > Click Add and Finish.

IP Address: IP tab > Enter IP Address of printer > Select protocol as LPD > Select installed driver in use > Click Add and Finish.

INSTALLING THE PRINTER FOR MAC

Download the App for Android or IOS from the following link.
[https://www.inkmasters.net.au/\[36ppm\]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-standard-two-sided-printing-fax-capability?search=mb2236t](https://www.inkmasters.net.au/[36ppm]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-standard-two-sided-printing-fax-capability?search=mb2236t)

In the app you can choose the Printer, then the document and Print easy!

AirPrint for Apple devices: On the image or document of the device, go to Share option and select

INSTALLING THE PRINTER FOR MAC

You can find the User Manual, Drivers, Mobile Print Apps under the Manuals and Drivers section of this link:
[https://www.inkmasters.net.au/\[36ppm\]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-standard-two-sided-printing-fax-capability?search=mb2236](https://www.inkmasters.net.au/[36ppm]-lexmark-laser-multifunction-wireless-monochrome-printer-mb2236adwe-with-a-2.8-inch-color-touch-screen-standard-two-sided-printing-fax-capability?search=mb2236)